

Project Specific Jumper Configuration: LSP PCB W/ MICROPROCESSOR P/N 14996

Jumper Placement & Configurations (CON 9 is @ Bottom of PCB)

Project # _____ - _____ Sales Order # _____ Date ____/____/____

Number of Units with this Configuration _____

NOTES: Setting JP 10 = Right & JP 9 = Right results in no timing operation.

Setting JP 10 = Left & JP 9 = Left results in separate timing for Circuits 1 & 2 based upon setting @ JP 8.

| JP # | Function | Project Setting | Options | Description |
|------|-------------------------------|-----------------|--|--|
| JP7 | Panic Output | | NONE Left Right | Standard Output: Output with Panic Mode Active Momentary Output W/ Panic Button Inverted Output with Panic Mode |
| JP10 | Circuit Configuration | | NONE Left Right | Output Circuits 1 & 2 operate independently Output CIR 2 if FAN, CIR 1 is standard Output CIR 1 & 2 operate by switch # 1 |
| JP 9 | Circuit Timing | | NONE Left Right | No Timing CIR 1 & 2 on timer CIR 2 on Timer as FAN |
| JP 8 | Time period on Circuit Timing | | NONE Left Right NONE Left Right | If JP9 = Left OR 1 Hr 2 Hr 3 Hrs If JP9 = Right & JP 10=Left (FAN) 15 MIN 0.5 Hr 1 Hr |
| JP 1 | EMS | | NONE Right Left | Active OFF (Input signal will turn OFF Output CIR 1 & 2) Active ON (Input signal require for CIR 1 & 2 to operate) Timer JP 6 Require to operate |
| JP 6 | EMS-Timer | | NONE Right Left | If JP 1 = NONE or GND (nothing happens) If JP 1 = (+) 8 Hr Timing 10 Hr Timing 12 Hr Timing |
| JP2 | EMS Input | | 1 Jumper @ Center 2 Jumpers | 24-vac Input Dry-contact Input |
| JP5 | ALARM Input | | 1 Jumper @ Center 2 Jumpers | 24-vac Input Dry-contact Input |
| JP4 | Panic/Alarm Input | | Jumper @ Lower Jumper @ Upper | Remote Panic places unit into Alarm State Remote Panic places unit into Panic State |
| JP3 | Panic Output | | 1 Jumper @ Center 2 Jumpers | Dry-contact Output 24-vac Output |

DOC# 14038

August 2015

ISIMET/MAPA, LLC
(903) 897-0737

103 W. CJ Wise Parkway
toll free (866) 897-0737
www.ISIMET.com

Naples, TX 7556
Fax (903) 897-0740